

AJAX

HOMESIREN



Wireless indoor siren that loudly notifies of an alarm during detector activation. It is installed indoors to warn of danger or deter intruders.



Ready to operate straight out the box: the battery is already installed, therefore there is no need to disassemble the siren. With one click, it can be connected to the hub in the mobile application. It can be mounted on the SmartBracket in just a few minutes.



Specification

Classification	Radio channel security sounder
Type of siren	Wireless
Installation method	Indoors
Type of notification	Sound
Connector for external LED	Available
Sound volume level	Adjustable, 81-105 dB at a distance of 1 m
Alarm length	Adjustable, 3-180 s
Indication of armed/ disarmed status	Yes
Alarm signal delivery time	0,15 s
Power supply	Battery: Two CR2 batteries Battery: Two CR123A batteries Power supply voltage: 3 V Battery life — up to 5 years
Jeweller radio technology	Communication range with central unit — up to 2,000 m in an open space Two-way communication between devices Operating frequencies — 868.0-868.6 MHz Self-adjusting RF output power — up to 20 mW Block encryption based on AES algorithm Device polling period — 12-300 s
Temperature sensor	Available
Operating temp range	From -10°C to +40°C
Permissible humidity	Up to 75%
Protection class of body	IP50
Anti-sabotage	Protection against fraud Jamming detection Tamper-resistant
Remote setting and testing	+
Dimensions	75x76x27mm
Weight	97 g
Certification	Grade 2, CE
Complete set	HomeSiren siren SmartBracket mounting panel Connector for LED indicator Two CR123A batteries (pre-installed) Installation set User's guide