

**REQUIRED CURRENT/LOAD FOR POWERING
DYNAMIC CCTV 12V DC/24V AC EXTERNAL
BOX CAMERA KITS**

MODEL	@ 24V AC	@ 12V DC
DTV-VLL PRO W6 FX KIT	864mA (heater on)	1.33A (heater on)
DTV-VLL PRO W6 FX KIT + DTV-IR50	2.11A (heater + IR on)	2.73A (heater + IR on)
DTV-VLL PRO W6 FX/METRO	704mA (heater on)	1.41A (heater on)
DTV-VLL PRO W6 FX KIT/METRO + DTV-IR50	1.96A (heater + IR on)	2.81A (heater + IR on)
SCB-2000P FX KIT	860mA (heater on)	1.29A (heater on)
SCB-2000P FX KIT + DTV-IR50	2.11A (heater + IR on)	2.69A (heater + IR on)
SCB-2000P FX KIT/ METRO	700mA (heater on)	1.37A (heater on)
SCB-2000P FX/METRO + DTV-IR50	1.95A (heater + IR on)	2.77A (heater + IR on)
DTV-27x W5 FX KIT	N/A	1.6A (heater on)
DTV-27x W5 FX KIT + DTV-IR50	N/A	3A (heater + IR on)
DTV-27x W5 FX KIT/METRO	N/A	1.68A (heater on)
DTV-27x W5 FX KIT/METRO + DTV-IR50	N/A	3.08A (heater + IR on)
SCB-2004P FX KIT	830mA (heater on)	1.25A (heater on)
SCB-2004P FX KIT + DTV-IR50	2.08A (heater + IR on)	2.65A (heater + IR on)
SCB-2004P FX KIT/METRO	670mA (heater on)	1.33A (heater on)
SCB-2004P FX KIT/METRO + DTV-IR50	1.92A (heater + IR on)	2.73A (heater + IR on)