













# TVI TURBO 4 DVR COMPARISON CHART

	DS-7200HQHI-K	DS-7200HUHI-K	DS-7200HTHI-K	DS-7300HQHI-K	DS-7316/32HUHI-K
<b>2MP RESOLUTION SUPPORT</b>	All channels 15fps	All channels 25fps	All channels 25fps	All channels 15fps	All channels 25fps
<b>5MP RESOLUTION SUPPORT</b>	X	All channels 12fps	All channels 20fps	X	All channels 12fps
<b>4K 8MP RESOLUTION SUPPORT</b>	X	Supported across all channels at 8fps from FW 3.5.30 except DS-7204HUHI-K	All channels 12fps	X	Supported across all channels at 8fps from FW 3.5.30 except DS-7332HUHI-K4
<b>IP CAMERA SUPPORT</b>	4CH = 1 IPC 8CH = 2 IPC 16CH = 2 IPC Supported	4CH = 2 IPC 8CH = 2 IPC 16CH = 2 IPC Supported	4CH = 2 IPC 8CH = 2 IPC Supported	4CH = up to 6 IPC 8CH = up to 10 IPC 16CH = up to 18 IPC 32CH = up to 40 IPC Supported	16CH = up to 18 IPC 32CH = up to 40 IPC Supported
<b>IP CAMERA RESOLUTION SUPPORT</b>	Up to 4MP	Up to 6MP	Up to 8MP	Up to 4MP 32ch = Up to 6MP	Up to 8MP
<b>ENHANCED VCA SUPPORT LINE CROSSING &amp; INTRUSION DETECTION ON ALL CHANNELS</b>	<ul style="list-style-type: none"> <li>Supports 4CH intrusion &amp; 4CH line crossing across all channels</li> <li>CVBS output is lost when this mode is enabled</li> </ul> 	<ul style="list-style-type: none"> <li>Supports 4CH intrusion &amp; 4CH line crossing across all channels</li> <li>5MP, 4MP &amp; 4K monitor output is lost when this mode is enabled</li> </ul> 	<ul style="list-style-type: none"> <li>Supports 4CH intrusion &amp; 4CH line crossing across all channels</li> </ul> 	<ul style="list-style-type: none"> <li>Supports 4CH intrusion &amp; 4CH line crossing across all channels</li> <li>CVBS output is lost when this mode is enabled</li> </ul> 	<ul style="list-style-type: none"> <li>Supports 4CH intrusion &amp; 4CH line crossing across all channels</li> <li>4K output resolution &amp; 4MP, 5MP input resolutions are lost in this mode</li> </ul> 
<b>INDEPENDENT HDMI &amp; VGA MONITOR OUTPUT</b>	X	X	VGA acts as call monitor 	32CH = 2 x HDMI outputs 	2 x Independent HDMI outputs
<b>CVBS OUTPUT</b>	Call monitor only 	Call monitor only 	Call monitor only 	Call monitor only 	Call monitor only 

## TVI TURBO 4 DVR COMPARISON CHART

	DS-7200HQHI-K	DS-7200HUHI-K	DS-7200HTHI-K	DS-7300HQHI-K	DS-7316/32HUHI-K
AUDIO INPUTS	1X	4X	4X	4X	4X
ALARM INPUTS	X	✓	✓	✓	✓
ONE KEY DISARMING FROM ALARM INPUT 1	X	✓	✓	✓	✓
KBD INPUT	X	X	X	✓	✓